

Field-Effect Transistor on SrTiO_3 with sputtered Al_2O_3 Gate Insulator

K. Ueno,^a I. H. Inoue, H. Akoh, M. Kawasaki,^b Y. Tokura,^c and H. Takagi^d

*Correlated Electron Research Center (CERC),
National Institute of Advanced Industrial Science
and Technology (AIST), Tsukuba 305-8562, Japan*

(Dated: February 2, 2008)

Abstract

A field-effect transistor that employs a perovskite-type SrTiO_3 single crystal as the semiconducting channel is revealed to function as n-type accumulation-mode device with characteristics similar to that of organic FET's. The device was fabricated at room temperature by sputter-deposition of amorphous Al_2O_3 films as a gate insulator on the SrTiO_3 substrate. The field-effect (FE) mobility is $0.1 \text{ cm}^2/\text{Vs}$ and on-off ratio exceeds 100 at room temperature. The temperature dependence of the FE mobility down to 2K shows a thermal-activation-type behavior with an activation energy of 0.6 eV.

PACS numbers: 85.30.Tv, 71.30.+h, 72.80.Ga, 73.40.Qv

Integrated circuits fully coordinated by functional oxide materials is still an eidolon of the next-generation electronic device. A transition-metal oxide, SrTiO_3 , has been providing us an ideal laboratory for the fundamental investigation to such oxide electronics, being widely used as one of the most important bulk substrates. It has a simple perovskite-type structure, and fairly smooth surface can be obtained through a chemical etching¹. This atomically smooth surface plays a substantial role in realizing a perfect epitaxial growth of two-dimensional heterostructures — a surpassing stage setting for the electronic-device application of the functional oxides. Overture to such expedition is to fabricate a naive metal-insulator-semiconductor field-effect transistor (MISFET) and let it function sufficiently. Nevertheless, although there have been a couple of reports on the simple MISFET with a SrTiO_3 channel^{2,3}, the on-off ratio for an applied field up to 1.5 MV/cm was only about two, which is far insufficient for a switching device.

In this Letter, we report a new approach to the fabrication of oxide devices. We fabricated an FET on a non-doped insulating SrTiO_3 single crystal, and revealed that it shows an exemplary FET characteristics unprecedented in any FET's made of perovskite-type oxide semiconductors so far⁴. Three chisels have carved the niche: one is that we have used a surface of the bulk SrTiO_3 single crystal as the channel. Another is that we have fabricated the FET structure by a so-called “dry process” with a stencil mask in order to prevent the surface of the SrTiO_3 from being degraded by the standard lithographic technique. The third is that we have selected amorphous Al_2O_3 films for the gate insulator which can be deposited on the SrTiO_3 surface without significant damages while keeping a large breakdown strength as well as large capacitance. However, with candid appreciation, our FET device [Fig.1(a)] is a reverse-engineering of that described in recent publications of Schön *et al.*, though the yet perplexing published results were declared to be fraudulent. Our work thus plays a role to give an insight into the feasibility of the claims as well as suggests essential requisites.

We used $10 \times 10 \times 0.5$ mm single-crystalline SrTiO_3 pieces, which were polished and etched by a vendor⁵ according to Ref[1]. Atomic force microscopy images of the surface exhibited a clear step-and-terrace structure. At first, source and drain electrodes of 20nm thickness aluminum were evaporated on the (100) surface of the SrTiO_3 substrate from a resistively heated tungsten boat through a Ni stencil mask at a rate of $5 \sim 10 \text{ \AA/s}$ under a pressure of 10^{-3} Pa . The aluminum electrodes for SrTiO_3 is reported to be preferable⁶. Actually, our electrodes yield an Ohmic contact on SrTiO_3 as clearly seen in the inset of

Fig.2. It is worth mentioning that we kept a considerable distance (~ 0.1 mm) between the stencil mask and the substrate during the evaporation in order to prevent the substrate from being contaminated by the mask. Then, the amorphous Al_2O_3 films of 50nm thickness were prepared by a radio-frequency magnetron sputtering with a 99.99% pure ceramic Al_2O_3 target ($50\text{mm}\phi$) in 2Pa flowing Ar gas. The base pressure of the sputtering chamber was better than 7×10^{-5} Pa. Sputtering power was 100 W and the target-to-substrate (TS) distance was fixed at 120 mm. This TS distance seems to be preposterously large, but is a key point to realize a *gentle* deposition to the substrate. Actually, the substrate temperature was at maximum 40°C during the deposition, even though we do not equip any cooling systems. At the final stage of the process, a gold wire was attached on the top of the Al_2O_3 film by conducting gold paint, which performs as the gate electrode, as shown in Fig.1 (b). Since our SrTiO_3 substrate was quite insulating, it is important that the gate electrode, *i.e.* the gold paint, must cover the entire channel region. Otherwise, even a narrow channel region uncovered by the gate electrode might prevent a current flowing between the source and drain electrodes.

The average breakdown voltage of the deposited Al_2O_3 film was 20 V, which corresponds to 4 MV/cm, and the leakage current at the breakdown was several nA. The capacitance per unit area C_i was $0.16 \mu\text{F}/\text{cm}^2$. Though we have attempted to optimize the sputtering condition over a wide range of deposition parameters, a maximum breakdown field has never exceeded 10 MV/cm. The source-drain current-voltage (I_{DS} - V_{DS}) characteristics with the $\text{Al}_2\text{O}_3/\text{SrTiO}_3$ FET with a channel length L and a width W of $25 \mu\text{m}$ and $300 \mu\text{m}$, respectively, were measured for different gate voltages V_{GS} . The I_{DS} - V_{GS} characteristics were measured for the temperature elevating from 2 to 400 K by 1 K or 2 K step; the measurement for each temperature took about 5 minutes. All measurements was carried out using the Agilent Technologies 4155C semiconductor parametric analyser.

The $\text{Al}_2\text{O}_3/\text{SrTiO}_3$ device shows a typical n-channel FET behavior as shown in Fig.2. Application of a positive gate bias greatly enhanced I_{DS} , while I_{DS} did not increase much for V_{GS} below 2 V. (No device we fabricated shows I_{DS} enhancement by applying a negative gate bias until the breakdown.) This enhancement of I_{DS} is due to the accumulation of negative carriers at the interface between the Al_2O_3 insulator and the SrTiO_3 substrate. A saturation of I_{DS} (pinch-off) was also observed for small values of V_{DS} . This pinch-off behavior indicates that the channel region is sufficiently depleted in this Al_2O_3 / SrTiO_3

FET, while the behavior has been hardly observed in other “dirty” FET’s such as that of amorphous Si. An on-off ratio is one of the most important parameters of FET devices. It is a ratio of I_{DS} for a given gate bias to that for zero gate bias. The on-off ratio exceeds 100, which was deduced for V_{GS} of 0 V and 4 V at V_{DS} of 1 V from the transfer characteristics shown in Fig.3 (a). This value is considerably larger than that of a similar device reported in literature³, because their device was fabricated at much higher temperatures and therefore suffered from a large background current even in the off-state. The threshold voltage of 1.5 V was also determined from Fig.3(a).

An interesting feature is that the field effect (FE) mobility μ_{FE} of our $\text{Al}_2\text{O}_3/\text{SrTiO}_3$ FET depends on V_{GS} up to the value as large as we could apply. In conventional FET, μ_{FE} can be well defined as

$$\mu_{FE}^{lin} = \frac{\partial I_{DS}}{\partial V_{GS}} \left(\frac{L}{C_i W V_{DS}} \right) \quad (1)$$

for large V_{GS} , *i.e.* the whole channel region is filled with the accumulated carriers. For V_{GS} near the threshold value V_{th} , μ_{FE} can be alternatively defined as

$$\mu_{FE}^{sat} = \left(\frac{\partial \sqrt{I_{DS}}}{\partial V_{GS}} \right)^2 \frac{2L}{C_i W} \quad (2)$$

and the channel is in pinch-off state. As shown in Fig.3 (b), both μ_{FE}^{lin} and μ_{FE}^{sat} increase monotonically with increasing V_{GS} above V_{th} . This large field dependence of the FE mobility is considered to be caused by the change of the field-induced carrier density; *i.e.*, the channel region changes drastically from the insulating state to the more conducting state. Similar feature was reported for several accumulation-mode FET’s on organics and amorphous-Si^{7,8}.

Since SrTiO_3 shows an insulator to metal transition at very low carrier concentration ($\sim 10^{18} \text{cm}^{-3}$) and the mobility of metallic SrTiO_3 increases with decreasing temperature,⁹ the temperature dependence of μ_{FE} of our $\text{Al}_2\text{O}_3 / \text{SrTiO}_3$ FET for various gate biases is worth exploring. When V_{GS} is much larger than V_{DS} , μ_{FE}^{lin} must be a good measure of the intrinsic μ_{FE} . Therefore, we used μ_{FE}^{lin} for V_{GS} above 4 V and V_{DS} of 1 V. The device measured here has L of 100 μm and W of 400 μm . As shown in Fig.4, no metallic behavior was observed for V_{GS} up to 9 V. (V_{GS} of 9 V corresponds to the field induced carrier density of 10^{13}cm^{-2} .) Indeed, below 270K, μ_{FE}^{lin} for such gate biases are dominated by the thermal activation, though from 180K to 2K the signal was smaller than the noise level of $10^{-7} \text{cm}^2/\text{Vs}$. The activation energy E_a between 270 K and 230 K was deduced to be 0.6 eV from the equation

$\mu_{FE} = \mu_0 \exp(-E_a/k_B T)$, where k_B is the Boltzmann constant. This value of E_a is independent of V_{GS} between 4 V and 9 V and is much larger than the bulk value of 0.14 eV, which was estimated by a time-of-flight technique¹⁰. Above 300 K, the μ_{FE} seems to be almost independent of V_{GS} , suggesting the transport mechanism was changed above room temperature. At higher temperatures above 320 K, since the gate leakage current increases rapidly with increasing temperature and becomes comparable to I_{DS} , it is not possible to reliably estimate the mobility.

The gate-dependent and thermal-activation-type mobility is often seen in the accumulation-mode FET of organics, cuprates and amorphous-Si^{7,8,11}. This is considered to reflect the nature of localized levels in the energy gap originated from dangling bonds or grain boundaries. In our Al₂O₃/SrTiO₃ device, the interface traps due to any surface defects or absorbed contaminants, which were inevitably introduced during the surface preparation by the chemical etching, contributed to the behavior of μ_{FE} . Indeed, there still needs a further investigation for the improvement of the device performance, among which the *in-situ* surface treatment by *e.g.* an annealing or a homoepitaxial deposition of a buffer layer between Al₂O₃ and SrTiO₃ should be considered.

In conclusion, we have demonstrated that an accumulation-mode MISFET devices with low threshold voltages and high on-off ratio can be realized using the surface of the bulk SrTiO₃ single crystal as a channel and the sputter-deposited amorphous Al₂O₃ as a gate insulator. The gentle deposition of the Al₂O₃ reduced the off-state conductance drastically and the on-off ratio exceeds 100 by the applied gate electric fields of 0.8 MV/cm. The FE mobility was found to be gate-bias dependent and thermal-activation-type as observed in other accumulation-mode FET's on several materials. We expect that more elaborate interface preparation would improve the device performance. However, the most important message we cast is that we have demonstrated the feasibility of the dry process with the sputtering of amorphous Al₂O₃ directly on the top of any substrates. With this recipe, one can fabricate other FET devices on any functional materials which are to be epitaxially grown on the SrTiO₃ substrates, and a gate electric field enables to tune the electronic properties of such materials — the second stage of the exploration for future oxide electronics.

We would like to thank A. Sawa, H. Sato, R. Kumai, T. Ito, T. Okuda, T. Shimizu, T. Yamada and Y. Ishii for their help and valuable discussions.

-
- ^a Electronic mail: kazunori-ueno@aist.go.jp; Also at: Department of Advanced Materials Science, University of Tokyo, Kashiwa, Chiba 277-8581, Japan
- ^b Also at: Institute for Materials Research, Tohoku University Sendai 980-8577, Japan
- ^c Also at: Department of Applied Physics, University of Tokyo, Bunkyo-ku, Tokyo 113-8656, Japan
- ^d Also at: Department of Advanced Materials Science, University of Tokyo, Kashiwa, Chiba 277-8581, Japan
- ¹ M. Kawasaki, K. Takahashi, T. Maeda, R. Tsuchiya, M. Shinohara, O. Ishiyama, T. Yonezawa, M. Yoshimoto, and H. Koinuma, *Science* **266**, 1540(1994).
- ² K. Gotoh, H. Takauchi, A. Yoshida, H. Tamura, and N. Yokoyama. DRC'94 IIIB-4, Boulder, CO/USA, June, 1994.
- ³ I. Pallecchi, G. Grassano, D. Marré, L. Pellegrino, M. Putti, and A. S. Siri, *Appl. Phys. Lett.* **78**, 2244 (2001).
- ⁴ Except for semiconductors, a field-effect transistor made of perovskite-type Mott-insulator was reported by Newns *et al.*, which shows switching characteristics similar to a conventional FET. D. M. Newns, J. A. Misewich, C. C. Tsuei, A. Gupta, B. A. Scott and A. Schrott, *Appl. Phys. Lett.* **73**, 780 (1998)
- ⁵ Shinkosha Co. Ltd., Yokohama ,Japan.
- ⁶ T. Shimizu, N. Gotoh, N. Shinozaki and H. Okushi, *Appl. Surf. Sci* **117-118**, 400(2002)
- ⁷ G. W. Neudeck and A. K. Malhotra, *J. Appl. Phys.* **46**, 2662 (1975).
- ⁸ G. Horowitz, R. Hajlaoui, and P. Delannoy, *J. Phys. III* **5**, 355 (1995).
- ⁹ O. N. Tufte and P. W. Chapman, *Phys. Rev.* **155**, 796 (1967).
- ¹⁰ D. Kéroack, Y. Lépine, and J. L. Brebner, *J. Phys. C* **17**, 833 (1984).
- ¹¹ A. Levy, J. P. Falck, M. A. Kastner, W. J. Gallagher, A. Gupta and A. W. Kleinsasser, *J. Appl. Phys.* **69**, 4439 (1991).

FIGURES


Fig 1 : (a) Schematic drawing of a field effect transistor (FET) structure fabricated on a single crystalline SrTiO_3 . The field induced carrier is expected to be accumulated at the interface between the amorphous Al_2O_3 insulator ($\sim 50\text{nm}$) and the SrTiO_3 single crystal. (b) Photograph of the FET device on SrTiO_3 . Before the Al_2O_3 deposition, a hillock of gold paint was heaped on each of the source (S) and drain (D) electrode. (Al electrodes are seen as dark squares.) After the Al_2O_3 deposition, the top of the hillock was scraped off and attached to the lead wire. The gate electrode (G) on the Al_2O_3 layer is the gold paint covering a part of the gap between the source and drain electrodes. The active channel is formed below the gate electrode underneath the Al_2O_3 film.

Fig 2 : Drain-source current I_{DS} plotted against the drain-source bias V_{DS} of the $\text{Al}_2\text{O}_3/\text{SrTiO}_3$ FET at 300K. A channel length and a width of the FET device were $25\mu\text{m}$ and $300\mu\text{m}$, respectively. The inset shows the blow-up of the I_{DS} - V_{DS} curve for $V_{GS} = 0\text{V}$.


Fig 3 : (a) The gate-source bias V_{GS} dependence of the drain-source current I_{DS} for a fixed drain-source bias $V_{DS} = +1\text{V}$ of the same device used for Fig.2. The on-off ratio between V_{GS} of 0V and 4V for V_{DS} of 1V exceeds 100. (b) V_{GS} dependence of the field effect mobility μ_{FE} . μ_{FE}^{lin} and μ_{FE}^{sat} were deduced from Fig.3 (a) by using Eq (1) and Eq (2), respectively. Both increases monotonically with V_{GS} and no saturation was observed even for large gate bias.

Fig 4 : Field-effect mobility μ_{FE} as a function of temperature. μ_{FE} was deduced by using Eq.(1) for the gate-source bias V_{GS} of 4V , 6V , 9V . The device has a channel length of $100\mu\text{m}$ and a width of $400\mu\text{m}$. The solid line corresponds to a thermally activated behavior with an activation energy E_a of 0.6eV .

(a)



(b)



0.5mm

